

Cable Prowler Cable Tester

Cable Prowler[™] combines the operations of a high-end cable and length measurement tester with the capacity to identify link status, link capability and PoE detection. All of this functionality is combined with internal memory to save, download and output results in full color.

Features and Benefits:

- High-resolution color display
- Save and print test reports
- TDR technology
- Link capability and status
- Link light
- Tests RJ45, RJ12/11 & Coax
- PoE detection
- Smart remotes
- · Color wire map
- · Tone generation
- Multilingual (English, Spanish, French, Italian, German)

Application:

- Cat 3/5e/6/6A
- Coax
- Telephone

Part # Description

	<u> </u>
TCB300	Cable Prowler [™] Cable Test Kit
TCB360K1	Cable Prowler™ PRO Test Kit
TCB400	Cable Prowler [™] Deluxe PRO Test Kit



Phone: 800.749.5783 Fax: 800.749.5784 California, USA

www.platinumtools.com

We Make Connections EZ!™

Cable Prowler™ PRO Test Kit

Full Color Cable Testing & Report Management

Cat 3/5e/6/6A, Coax and Telephone

Cable Prowler Tester

and printed

router port

load test for voltage drop

View saved cable tests

and German

(IEEE802.3af/at requirements)

network and telephone cables

Full color graphical wire-mapping

Generates selectable tones on selected pins for use

• Language selections of English, French, Spanish, Italian,

in feet or meters

· Easy viewing in any environment

PLATINUM 3001 **#1-8 Coax Remote Set** ID/MAP 8 video (coax) cables at once. Numbered custom F remotes 1 thru 8 for easy identification Test results can be named, saved, viewed · Measures cable length & distance to faults Detects and reports current link speed and link capabilities for active Ethernet drops up Link light to identify location on a hub/switch/ • Tests Ethernet cable configuration and verifies connectivity while conducting tests for opens, shorts, miswires, split pairs and reverses • Detects presence of PoE and class of PoE with Supports up to 8 testing and ID remotes for

#1-8 Smart Remote Set

- Test & Map/ID voice/data simultaneously
- Cat6, Cat6A, Cat5e, Cat5, Cat4 and Cat3 cables
- Shielded and unshielded cables

#1-12 Data Remote Set **Adapters** • F Female-to-F Female - (Qtv 2)

• ID/MAP 12 data (twisted pair) cables or data ports/jacks at once. Numbered custom RJ45 remotes 1 thru 12 for easy identification.

Cables

- Micro USB Cable: Connects Cable Prowler to computer for exporting test results
- No-Fault Cable:

7.5" Special RJ12 to RJ12 The No-Fault Cable uses no-fault RJ12 connectors on both ends to assure no damage to the RJ45 jacks. It is the ideal patch cable to use when mapping or shooting tone.

RJ45 Port Saver:

Extend the life of your tester by using the RJ45 Port Saver as your sacrificial cable. This eliminates the wear and tear from constantly plugging in and out of the tester port.


• Tone Cable RJ45/Alligator: Use when shooting tone via the data port. Cable conductors are terminated on contact #1 and #2, so program your Cable Prowler to shoot tone on pair 1 and 2.

Test Displays

□ T568B

Pass






• BNC Female-to-F Female - (Qty 1)

• BNC Female-to-F Male - (Qtv 1)

Link Light Θ*

Network PoE Testing

PoE + A 25.5W Max 57.9 V Min Load 56.1 V Max Load



www.platinumtools.com

We Make Connections EZ!™

Cable Prowler Cable Test Kit

P/N TCB300

Kit Includes:

- Cable Prowler[™] Main Unit
- Cable Tester Smart Remote, #1
- ID Only Coax Remotes, #1-5
- ID Only Network Remotes, #1-5
- F Connector Coupler F81
- No-Fault, RJ12 Cable (2)
- Micro USB Cable
- Alkaline AA Batteries
- · Hanging Pouch



Cable Prowler Deluxe PRO Test Kit

P/N TCB400

Kit Includes:

- Cable Prowler[™] Main Unit
- Cable Tester Smart Remotes, #1-8
- ID Only Coax Remotes, #1-20
- ID Only Network Remotes, #1-20
- ToneSeeker[™] Tone Tracer Probe
- F Connector Coupler F81
- No-Fault, RJ12 Cable (2)
- Micro USB Cable
- Alkaline AA Batteries
- Large Shoulder Bag



Specifications

Measurement	Time Domain Reflectometry (TDR)
Technology	, ,
Cable Measurements	Cable Testing and ID: up to 1000 ft (305 m) Split Pair Detection: 3 ft (1 m) to 1,000 ft (305 m) Length Measurement: 0 to 1,500 ft (457 m), ± (5%+1 ft) Supports 8 continuity and ID number remotes (RJ45) Supports 20 RJ45 and 20 F connector ID only remotes
Power over Ethernet	Tests for IEEE 802.3af and IEEE 802.3at (PoE Plus compliant PoE Tests for classes and loads cable up to 25.5 watts (at class 4) Identifies Mode A or B (pairs with PoE)
Active Ethernet	Indicates advertised speeds of 10/100/1000base-T half or full duplex. Can link to network at 10/100base-T
Maximum Voltage	RJ Jack: 66 VDC or 55 VAC F Connector: 50 VDC or VAC
	Refers to the max voltage that can be applied to any 2 connector pins without damaging the tester.
Save Test Results	Stores up to 250 cable or network tests with user defined names
Tone Generation	Tone Frequencies: 730 Hz and 1440 Hz
Languages	English, French, Spanish, German, and Italian
Battery Life	For 6 x AA, 9VDC, 2,200 mA-hr (typical) alkaline battery: Operating – 20 hours typically Standby – 1.5 years typically (200uA max standby current) Batteries are included
Altitude	10,000 ft (3048 m) operating
Temperature	Operating: 32 to 122°F (0 to 50°C) Storage: -22 to +140°F (-30 to 60°C)
Humidity	10 to 90% non-condensing
Enclosure	High-strength PC/ABS plastic with V0 rating with boot Withstands 4 foot drops onto concrete
Size	1.85"H x 3.6"W x 6.8"L (4.7 x 9.15 x 17.3 cm)
Weight	With batteries: 1 lb 2 oz (510 g)
Safety Compliances	CW
Warranty	1 Year

Cable Prowler PRO Test Kit P/N TCB360K1

Kit Includes:

- Cable Prowler[™] Main Unit
- Cable Tester Smart Remotes, #1-8
- ID Only Coax Remotes, #1-8
- ID Only Network Remotes, #1-12
- Micro USB Cable
- Cable Assemby, RJ45 to Alligator Clip
- No-Fault, RJ12 Cable (2)
- RJ45 Port Saver
- F Connector Coupler F81
- BNC Adapter Kit
- Alkaline AA Batteries
- Durable Plastic Case





Phone: 800.749.5783 Fax: 800.749.5784 California, USA

www.platinumtools.com

We Make Connections EZ!™